

Veeder Root® TLS-250 External Printer Kit

Enclosed is a complete pre-configured kit to retrofit a TLS-250 console with an external high quality Citizen dot matrix printer. This replaces the internal original equipment thermal printer, which is now obsolete. Thank you for purchasing PMP quality products.

Installation Procedure:

- 1) Power down the TLS-250.
- 2) Remove the upper and lower screws on the right hand side of the TLS-250 display 'door'.
- 3) Open the door and remove the black and yellow (or red) wires of the original printer from positions 7 or (common) & 8 or (print) on the upper terminal strip.
- 4) Unplug the 3-pin AC power connector from J1 on the motherboard. The old printer is now disconnected and can be left inside the console.
- 5) Find a convenient and safe location for the new printer within ten feet of the TLS-250. A shelf mount kit is available from PMP if needed.
- 6) Knock out one of the 3/8" access plugs on the bottom of the TLS-250 chassis and install the included 3/8" strain relief.
- 7) Route the 10' gray driver cable from printer through the strain relief. You can store excess cable in the area that the old printer now occupies, if necessary.
- 8) Fasten the black wire to #7 or (common), and the red to #8 or (print) on the upper terminal strip. Tighten the two screws on the strain relief.
- 9) Plug in and power up the printer, then load in the enclosed ribbon cartridge and paper roll.
- 10) Power up the TLS-250. Hit the 'print' button on the TLS-250 to test.

Troubleshooting Tips:

- A) If the printer prints 'Power Down (Data In Buffer)' in red and/or random characters, and not TLS-250 data, power down just the printer, then power it back up again while you hold down the 'sel' button.
- B) If the green 'error' light blinks, make sure paper is properly loaded, and make sure the paper roll is inserted squarely into the rear of the printer.

For further assistance, please call PMP Corporation at 1-800-243-6628.

All product or company's names, trade names, trademarks, parts numbers and part descriptions may be the trademarks of their respective owners, and are used for reference or identification purposes only. PMP does not claim any right to or affiliation with such owners. The PMP product described here is manufactured or remanufactured and sold by PMP and is not the product of any other identified manufacturer.



PMP CORPORATION
P.O. Box 422 - 25 Security Drive
Avon, CT 06001

Local: 860-677-9656
Toll Free: 800-243-6628
Toll Free Fax: 888-674-0196
Web: www.pmp-corp.com
E-mail: sales@pmp-corp.com

